

Ports used by IP-INTEGRA SIP-server:

Protocol	Port (Default)	Short Description	Port Forwarding Required
UDP	15060	IP-INTEGRA VoIP System	YES. If you intend to use VoIP providers, remote extensions and mobile applications. NOTE: Recommend changing to port 15060 because of ALG conflict with some private routers.
TCP	8090	HTTPS Communication and Remote provisioning	YES. If you intend to remote setup and update remote extensions and mobile applications.
UDP	9000-9500	IP-INTEGRA Media Server (RTP)	YES. If you intend to use VoIP providers, remote extensions and mobile applications. NOTE: Number of ports are double of number of parallel calls. Default setup is 500 ports and 250 parallel calls.
Whitelist following addresses and domains:			
support.freund.ba			89.239.196.190
cloud.freund.ba			51.38.114.236

NOTE 1: Please make sure that there is access to internet by controlling IP-Address / External IP status on IP-INTEGRA SIP-server dashboard.

NOTE 2: If SIP-ALG on router is active, please turn it OFF.

